

Eaton 248439

Eaton Distribution parts. Shunt release, 110-415V, 1HP

General specifications

| | |
|-----------------------------|--------------------------|
| PRODUCT NAME | Eaton Distribution parts |
| CATALOG NUMBER | 248439 |
| EAN | 4015082484392 |
| PRODUCT LENGTH/DEPTH | 80 mm |
| PRODUCT HEIGHT | 75 mm |
| PRODUCT WIDTH | 26.2 mm |
| PRODUCT WEIGHT | 0.087 kg |
| COMPLIANCES | RoHS conform |
| CERTIFICATIONS | EN45545-2 IEC 61373 |
| MODEL CODE | ZP-ASA/230 |

Specificații produs

| | |
|--|---|
| USED WITH | Shunt releases Accessory for combined residual current/power circuit breaker Accessory Accessory for miniature circuit breaker |
| ACCESSORY/SPARE PART TYPE | Shunt release |
| MOUNTING METHOD | For fitting on left to: FAZ, FRBmM-1N, Z-MS |
| ADDITIONAL EQUIPMENT REQUIRED | Shunt release (for power circuit breaker) |
| AMBIENT OPERATING TEMPERATURE - MAX | 75 °C |
| AMBIENT OPERATING TEMPERATURE - MIN | -35 °C |
| ASSEMBLY WIDTH | 1 |
| NUMBER OF CONTACTS (CHANGE-OVER CONTACTS) | 0 |
| NUMBER OF CONTACTS (NORMALLY CLOSED CONTACTS) | 1 |
| NUMBER OF CONTACTS (NORMALLY OPEN CONTACTS) | 1 |
| NUMBER OF POLES AT MAIN CONTACT UNIT - MAX | 1 |
| NUMBER OF SWITCHES (FAULT SIGNAL) | 0 |
| VOLTAGE TYPE | AC |
| FUNCTIONS | Shunt release (for power circuit breaker) |
| DEVICE FITTING | Other |
| TYPE | <ul style="list-style-type: none">• Accessory• Accessory for combined residual current/power circuit breaker• Accessory for miniature circuit breaker |
| APPLICATION | Switchgear for industrial and advanced commercial applications |
| RATED OPERATIONAL VOLTAGE (UE) - MAX | 230 V |

Resurse

| | |
|------------|---|
| DESENE | eaton-3d-drawing-zp-asa-mont.jpg eaton-3d-drawing-mont-usa-1.jpg |
| MCAD MODEL | faz_xaa.stp |

**SUITABLE FOR CURRENT
OF MAIN CONTACT UNIT** 2.1 A
- MAX

DENUMIREA PROIECTULUI:

NUMĂRUL PROIECTULUI:

PREGĂTIT DE:

DATA:



Eaton Corporation plc Eaton House
30 Pembroke Road
Dublin 4, Irlanda
Eaton.com

© 2026 Eaton. Toate drepturile rezervate

Urmăriți-ne pe rețelele de socializare
pentru a obține cele mai noi
informații despre produse și
asistență.

